

Product Update Notice

Upgraded IG1 & IG3 LED Well Lights

New COB Light Engine.

More CCT & CRI choices.

More optics choices.

More lumen output.

Same quality and reliability.



Precision cast and machined LED lighting fixture with 12V input LED Light Engine (COB with integrated driver module). Modular industry standard components allow for simple field replacement and future upgrade. Rugged cast bronze faceplate and collar is suitable for the most corrosive of environments and is designed for in ground mounted up lighting in wet location landscape applications.

Features ¹

- Industry standard COB LED components used to simplify maintenance and future upgrades.
- Field replaceable internal components and connectors on wiring connections for easy installation and maintenance.
- Light engine is enclosed in a water tight body that uses high temperature silicone O-rings and a water tight cable exit to ensure a wet location rating.
- Stainless steel brackets provide simple hot-aiming convenience.
- Standard housing collar is suitable for concrete pour or landscape applications.
- Faceplates available in multiple round or square styles with tamper-proof, captive screws (optional in square faceplate).

Specifications ¹

- Input voltage: 12VAC (±10%).
- Lumen Output (nominal): 400lm, 700lm, 1000lm. ²
- Field replaceable optics: 15°, 24°, 36°, 55°, 65°.
- Color temperature: 2700K, 3000K, 3500K, 4000K.
- CRI options: 80, 90.
- Dimming: Phase dimming (ELV, MLV). ³
- L70 > 40,000 hours.
- Protection (driver): short circuit, overload, thermal, auto-reset.

1. Features and Specifications subject to change without notice. Please see latest specification sheet(s) on website for latest information.
2. Lumen Output (nominal) is ideal lumen output of light engine only in lab conditions. Actual fixture output will vary with fixture/cap type, material, lens/optics options, CRI, CCT, mounting, orientation, and environmental conditions. For more accurate information, see fixture photometry files on website.
3. Contact Vision3 for dimmer compatibility.